

Change Notice

EB, M, MB2400 & MB2500 Series

Changes for AT617 LED & AT212 Bezel

Type of Change:

- Engineering Part Number
 Product Appearance

1. The AT617 LEDs used with M Rockers and EB, MB2400 and MB2500 Pushbuttons will be undergoing changes. This will result in revisions to some of the dimensions and electrical values, and will apply to red, yellow and green LEDs for standard or custom switches. Following is the comparison between the specifications before and after the changes.

Revisions for the AT212 Bezel are on page 2, with the affected standard part numbers.




EB Series Pushbutton with AT212 Bezel & AT617 LEDs

CHANGES TO LED SPECIFICATIONS FOR AT617

Electrical specifications are determined at a basic temperature of 25°C.		Before Change			After Change		
		C	E	F	C	E	F
	Color	Red	Yellow	Green	Red	Yellow	Green
Maximum Forward Current	I_{FM}	30mA	30mA	25mA	30mA	30mA	30mA
Typical Forward Current	I_F	20mA	20mA	20mA	20mA	20mA	20mA
Forward Voltage	V_F	2.0V	2.1V	2.25V	2.1V	2.1V	2.2V
		$I_F = 20\text{mA}$	$I_F = 20\text{mA}$	$I_F = 20\text{mA}$	$I_F = 20\text{mA}$	$I_F = 20\text{mA}$	$I_F = 20\text{mA}$
Maximum Reverse Voltage	V_{RM}	5V	5V	5V	5V	5V	5V
Current Reduction Rate Above 25°C	ΔI_F	0.40mA/°C	0.40mA/°C	0.33mA/°C	0.40mA/°C	0.40mA/°C	0.40mA/°C
Ambient Temperature Range		-15°C ~ +70°C			-15°C ~ +70°C		

Notes

- The LED circuit is isolated and requires an external power source.
- If the source voltage is greater than the LED's rated voltage, a ballast resistor must be connected in series with the LED. The resistor value can be calculated by using the formula shown here.
- Contact information is below if more details are needed.



$$R = \frac{E - V_F}{I_F}$$

Where: R = Resistor Value (Ohms)
 E = Source Voltage (V)
 V_F = Forward Voltage (V)
 I_F = Forward Current (A)

Before Change	After Change

Effective Date

Changes for AT617 LEDs will be effective June 2020.

NKK
SWITCHES

www.nkkswitches.com • 1.877.2BUYNKK (228.9655)

7850 East Gelding Drive • Scottsdale, AZ 85260 • Telephone 480.991.0942 • Fax 480.998.1435

Change Notice EB, M, MB2400 & MB2500 Series

Changes for AT617 LED & AT212 Bezel

Type of Change:

- Engineering Part Number
 Product Appearance



The AT212 Bezel is slated for changes that will accommodate the AT617 LEDs.

2. The AT212 bezels used with M Rockers and EB, MB2400 and MB2500 Pushbuttons will be undergoing changes. This will result in some dimension revisions to accommodate the modified AT617 LEDs. Following is the comparison between the dimensions before and after the changes.

CHANGES FOR AT212 BEZEL			
Before Change		After Change	
<p>Top View</p>	<p>Side View</p>	<p>Top View</p>	<p>Side View</p>

Notes

- The new AT617 LEDs will only fit with the revised AT212 bezel.
- Contact information is below if more details are needed.

Effected Standard Part Numbers				
AT212 Bezel	AT617 LED	EB Pushbuttons	M Rockers	M Rockers
AT212A	AT617C	EB2011-A-J23AFC	M2012TJA01-FH-3A-FC	M2022TJW01-FC-3A-FC
---	AT617E	EB2011G-B-J23AFE	M2012TJG01-FA-3A-CF	M2022TJW03-GA-3A-FE
---	AT617F	EB2085-B-J33AFF	M2012TJW01-FA-3A-CF	M2023TJW01-FA-3A-CC
---	---	EB2085G-B-J33AEF	M2013TJW01-FA-3A-CC	M2023TJW01-GC-3A-FF
---	---	EB2085G-B-J33AFF	M2018TJG01-FB-3A-EE	M2023TJW03-FA-3A-CF
---	---	---	M2018TJW01-FA-3A-CF	M2023TJW03-FC-3A-CF
---	---	---	M2022TJG01-FB-3A-EE	M2029TJW01-FC-3A-CE

Effective Date

Changes for AT212 bezels will be effective June 2020.

NKK
SWITCHES

www.nkkswitches.com • 1.877.2BUYNKK (228.9655)

7850 East Gelding Drive • Scottsdale, AZ 85260 • Telephone 480.991.0942 • Fax 480.998.1435