## Change Notice NP01 Series Illuminated Pushbuttons

## Change of Single Color LED Specifications

Type of Change:

- ☑ Engineering □ Part Number
- Product Appearance

The NP01 Series Illuminated Pushbuttons will have changes to the single color LEDs. The change will effect all single color models, both standard and custom. Differences in the LED specification values are outlined in the following table.



**NP01 Pushbutton** 

NP0115HG03LF-JB

NP0115HG03LF-JF

Electrical Specifications for NP01 Single Color LED								
Electrical specifications are determined at a basic temperature of 25°C.		Before Change			After Change			
ATTENTION ELECTROSTATIC SENSITIVE DEVICES	Color	C Red	D Amber	<b>F</b> Green	C Red	D Amber	<b>F</b> Green	
Maximum Forward Current	I <sub>FM</sub>	50mA	50mA	30mA	30mA	30mA	25mA	
Typical Forward Current	I <sub>F</sub>	20mA	20mA	20mA	20mA	20mA	16mA	
Forward Voltage	V <sub>F</sub>	2.0V	2.1V	3.5V	1.95V	2.0V	3.3V	
Maximum Reverse Voltage	V <sub>RM</sub>	5V	5V	5V	5V	5V	5V	
Current Reduction Rate	$\Delta I_{\rm F}$	0.88mA/°C above 40°C	0.88mA/°C above 40°C	0.48mA/°C above 30°C	0.41mA/°C above 25°C	0.38mA/°C above 25°C	0.33mA/°C above 25°C	
Ambient Temperature Range -25° ~			-25° ~ +50°C	50°C –25° ~ +50°C				
Red or Green LEDs $LC1 \\ (+) \\ 0 \\ L1 (-) \\ (+) \\ 0 \\ L1 (-) \\ (+) \\ (+) \\ 0 \\ L1 (-) \\ (+) \\ ($								
<ul> <li>Notes</li> <li>LEDs are an integral part of the switch and are not available separately.</li> <li>If the source voltage exceeds the rated voltage, a ballast resistor is required. The resistor value can be calculated by using the formula shown here.</li> <li>The changes to single color LEDs do not affect any external dimensions of the switches.</li> <li>Contact the factory if further details are needed.</li> </ul>								
NP01 Part Numbers Effected by Single LED Specification Changes								
NP0115AG03LC-JB	N	P0115AG03LD-	JD	NP0115HG03	LC-JB	NP0115HG	03LD-JD	

NP0115AG03LD-JB					
Effective Date					

NP0115AG03LC-JC

Changes to Single Color LEDs will be effective October 2015.

NP0115AG03LF-JB

NP0115AG03LF-JF

## SUITCHES http://www

http://www.nkkswitches.com • 1.877.2BUYNKK (228.9655)

NP0115HG03LC-JC

NP0115HG03LD-JB

7850 East Gelding Drive • Scottsdale, AZ 85260 • Telephone 480.991.0942 • Fax 480.998.1435

2015/10/21 Engineering Department